

CENTER 220/221/222 Low Cost Mini Clamp Meter

CENTER 220 is our low cost mini clamp series. 220 is a current probe with read out. 221 is added with voltage and continuity functions. 222 is an AC/DC clamp meter.

FEATURES:

- Pocket Size
- 4 digits Display (222)
- Peak Hold Function (222)
- Data Hold Function
- 0.1A Resolution at Full Range (222)
- Touch Zero Function (222)
- Autoranging (221/222)
- Auto Power Off (222)



SPECIFICATIONS

Function	Range	Resolution	Accuracy
ACA	200A ~ 600A	0.1A ~ 1A	±2%rdg+5dpts
DCA	600A	0.1A	±2%rdg+5dpts
ACV	200V ~ 600V	0.1V ~ 1V	±1.5%rdg+5dpts
DCV	600V	0.1V	±1%rdg+2dpts
Ohms	200Ω	0.1Ω	±1.9%rdg+3dpts
🔊)	Active Sound Level: ≤40Q		

Display	3-1/2, 4 digital Liquid display
Sampling Rate	2 times/sec
Battery	1.5V, size AAA battery x 2
Dimensions	187x50x29 mm
Weight	approx. 210g
Jaw Opening Diameter	25mm
Peak Hold Capture Time	10ms

CENTER 223 High Resolution Mini AC/DC Clamp Meter

CENTER 223 is a high resolution AC/DC clamp meter. With resolution of 1mA and span of 100A, this tester is great for appliance installation or for car applications.



FEATURES:

- Analog Signal Output Function
- Pocket Size
- 4 digits Display
- Peak Hold Function
- Data Hold Function
- 1mA Resolution
- Touch Zero Function
- Autoranging
- Auto Power Off

SPECIFICATIONS

Function	Range	Resolution	Accuracy
ACA	10A ~ 100A	1mA ~ 10mA	±2%rdg+10dpts
DCA	10A ~ 100A	1mA ~ 10mA	±2.5%rdg+10dpts
ACV	600V	0.1V	±1.5%rdg+5dpts
DCV	600V	0.1V	±1%rdg+2dpts
Ohms	10KΩ	1Ω	±1%rdg+3dpts
🔊)	Active Sound Level: ≤100Q		
Analog Output: 10mV/Amp ; Frequency Response: 20KHz			

Display	4 digital Liquid display
Sampling Rate	2 times/sec
Battery	1.5V, size AAA battery x 2
Dimensions	202x70x34 mm
Weight	approx. 180g
Jaw Opening Diameter	12.5 mm



CENTER®
CENTER TECHNOLOGY CORP.

4/F., NO.415, Jung-Jeng Rd., 238 Shu-Lin, Taipei, Taiwan
 TEL: 886-2-26763926 E-Mail: center@centertek.com
 FAX: 886-2-26763925 http://www.centertek.com

* The specifications and other information in this catalogue are subject to change without prior notice.